

Specifications:

Brand new & high quality!

Dual measurement of AC voltage, AC current(It can't be used for measuring the AC power converted from a DC power with an inverter)

Voltage Measuring Range: AC 80 ~ 260V Current Measuring Range: AC 0 ~ 20A Active Power Measuring Range: 0 ~ 4.5kW

The meter can only measure the active power(real power). It doesn't show Apparent power which includes reactive power and active power. For more information about the difference,

please read this: LINK

Energy Measuring Range: 0 ~ 9999kWh Operating Temperature: -10 °C ~65 °C Operating Humidity: 35~85% RH

Dimensions:9cm * 5cm * 2.45cm/3.54" * 1.97" * 0.96"